# Photoelectrics Diffuse-reflective Type EO1804.PAS, DC, Metal-housing

#### • Range: 400 mm adjustable

- Modulated, infrared light
- Supply voltage: 10 to 40 VDC
  - Output: 200 mA NPN or PNP
- Make and break switching function, LED indication
- Protection: Reverse polarity, short-circuit, transients
- High immunity to ambient light
- Heavy duty M18 metal housing, IP67
- Cable and plug versions

# ( ( 🖲 🕄

#### **Product Description**

The EO1804 is a family of general purpose Diffuse-reflective sensors in a short M18 metal housing for heavy duty applications. They are useful for simple applications where a basic sensor provides adequate sensing performance. The sensors are easy to adjust with 270° single turn potentiometer. The output is a 4-wire complementary (NO and NC) output in NPN (current sinking) or PNP (current souring).

Ordering Key	EO 18 04 NPA S-1
Туре	
Housing diameter —	
Range	
Output type	
Housing material	
Connection type —	

### **Type Selection**

Housing diameter	Rated operating dist. (S <sub>n</sub> )	Ordering no. NPN/cable Make & break swit.	Ordering no. NPN/plug Make & break swit.	Ordering no. PNP/cable Make & break swit.	Ordering no. PNP/plug Make & break swit.
M18	400 mm	EO 1804 NPAS	EO 1804 NPAS-1	EO 1804 PPAS	EO 1804 PPAS-1

#### **Specifications**

Rated operating dist. (S <sub>n</sub> ) Adjustable	Up to 400 mm Reference target: Kodak test card R27, white, 90% reflectivity 200 x 200 mm
Sensitivity	270° turn potentiometer
Temperature drift	0.4%/K
Hysteresis (H) (Differential travel)	3 to 20%
Rated operational volt. $(U_B)$	10 to 40 VDC (ripple included)
Ripple (U <sub>rpp</sub> )	Max. 10%
Output current Continuous (I <sub>e</sub> ) Short-time (I)	Max. 200 mA 200 mA, max. load capacity 100 nF
No load supply current (I <sub>o</sub> )	Max. 20 mA
Min. operational current (I <sub>m</sub> )	0.5 mA
OFF-state current (I <sub>r</sub> )	Max. 100 μA
Voltage drop (U <sub>d</sub> )	Max. 2.5 V @ 200 mA
Protection	Reverse polarity, short circuit, transients
Transient voltage	Max. 1 kV/0.5 J
Light source	GaAlAs LED, 880 nm

Light type	Infrared, modulated synchronized		
Sensing angle	$\pm$ 25° at <sup>1</sup> / <sub>2</sub> range		
Ambient light	Max. 10,000 lux		
Operating frequency (f)	120 Hz, light/dark ratio 1:2		
Response time			
OFF-ON (t <sub>on</sub> )	≤ 3.2 ms		
ON-OFF (t <sub>off</sub> )	≤ 5 ms		
Power ON delay $(t_v)$	Typ. 100 ms		
Indication function Output ON	Dark and light (complementary switch) LED, yellow		
Environment			
Overvoltage category Pollution degree Degree of protection	III (IEC 60664/60664A; 60947-1) 3 (IEC 60664/60664A; 60947-1) IP 67 (IEC 60529; 60947-1)		
Temperature			
Operating Storage	-20° to +60°C (-4° to 140°F) -30° to + 70°C (-22° to 158°F)		
Vibration	10 to 150 Hz, 0.5 mm/7.5 g (IEC 60068-2-6)		
Shock	2 x 1 m & 100 x 0.5 m (IEC 60068-2-32)		
Dielectric voltage	500 VAC (IEC 60365-4-41)		








Nickel plated brass Luran <sup>®</sup> , black Polyester, black Nickel plated brass
Grey, 2 m, 4 x 0.35 mm <sup>2</sup> oilproof PVC M12 x 1 CON.14NF series
140 g 55 g
UL, CSA Yes

#### **Specifications** (cont.)

#### + 1 BN 4 BK 2 WH 3 BU


Wiring Diagrams



# **Operation Diagram**

Power supply				
Object present, light received	l			
Output ON: Make switching (NO) BK (4)	l		⊦Tv⊣	
Break switching (NC) WH (2)		1		


# **Dimensions**



# **Delivery Contents**

- Photoelectric switch EO1804.PAS(-1)
- 2 nuts
- Packaging: plastic bag

# **Detection Diagram**



# **Accessories**

- MB18A
- Connector type CON.14NF.. series
  Screw driver for adjustments: 77-000
- APA18-RAR