



**Current transformer HF5, 1250A/1A**

**Part no. HF5-1250/1A**  
**Catalog No. 741E0038**

Similar to illustration

**Technical data ETIM 7.0**

|  |  |    |                                |
|--|--|----|--------------------------------|
| Low-voltage industrial components (EG000017) / Current transformer (EC002048)  |  |    |                                |
| Electric engineering, automation, process control engineering / Signal processing / Transformer / Current transformer (ecl@ss10.0.1-27-21-09-02 [AAB626014]) |  |    |                                |
| Model  |  |    | Through-feed current converter |
| Primary rated current  |  | A  | 1250                           |
| Secondary rated current  |  | A  | 1                              |
| Secondary rated apparent power   |  | VA | 30                             |
| Accuracy class   |  |    | 0.5                            |
| Over current limiting factor   |  |    | FS 5                           |
| Calibrated   |  |    | No                             |
| With shock protection  |  |    | No                             |
| Height opening   |  | mm | 13                             |
| Width opening  |  | mm | 61                             |
| Opening diameter   |  | mm | 39                             |
| Snap mounting  |  |    | Yes                            |
| With copper rail   |  |    | No                             |
| Secondary connection   |  |    | Screw connection               |
| Number of primary inputs   |  |    | 1                              |