



Fuse base, low voltage, 16 A, AC 400 V, D01, 1P, IEC, screw mounting, suitable for 1.5 - 4 mm² connecting leads

Part no. SICHERUNGSUNTERTEIL D01 E14 1POL
Catalog No. FN01C

Delivery program

Product range			Fuse accessory
Basic function			Fuse-base
Field of application			low voltage
Rated current	I	A	16
Rated voltage			AC 400 V
Construction size			D01
Description			screw mounting suitable for 1.5 - 4 mm ² connecting leads
Number of poles			1P
usable for size/applications			D01 E14 screw
Standard/Approval			IEC
Supplied with			protection cover

Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / D0-system fuse base (EC001644)			
Electric engineering, automation, process control engineering / Electrical installation, device / Safety fuse systems / Neozed fuse base (ecl@ss10.0.1-27-14-21-20 [ACN355011])			
Number of poles			1
Construction size			D01
Material			Porcelain
Version with cover			Yes
Mounting method			Screw mounting
Rated voltage		V	400
Rated current		A	16