DATASHEET - NZM4-4-XKV2P

Terminal jumper, with cover, 4p, /2p



Part no.	NZM4-4-XKV2P
	119888
EL Number	4356085
(Norway)	

(itorivay)	
General specifications	
Product name	Eaton Moeller series NZM link kit
Part no.	NZM4-4-XKV2P
EAN	4015081177363
Product Length/Depth	276 millimetre
Product height	125 millimetre
Product width	216 millimetre
Product weight	4.82 kilogram
Compliances	UL489B IEC RoHS conform
Product Tradename	NZM
Product Type	Accessories
Product Sub Type	Link kit
Delivery program	
Туре	Accessory DC link kit Terminal
Number of poles	Two-pole
Amperage Rating	1400 A (40 °C), 1260 A (65 °C)
Special features	Jumper kit with cover IP2X
Frame	NZM4
Suitable for	Four-pole
Used with	N4-4-800(1000)(1100)-S1(-S15)-PV-NA
	N4-4S1(-S15)-DC
Technical Data - Mechanical	
Special features	Jumper kit with cover IP2X
Design verification as per IEC/EN 61439	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will
10.11 Short-circuit rating	provide heat dissipation data for the devices. Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.		
Additional information			
Model	Other		
Technical data ETIM 9.0			
Low-voltage industrial components (EG000017) / Wiring set for power circuit breaker (EC002050)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Wiring set for circuit breaker (ecl@ss13-27-37-04-24 [ACN957016])			

 Suitable for number of poles
 4

 Model
 Other