

Illuminated ring, LED, 60mm, 230VAC, yellow

Part no. M22-XPV60-Y-230
138280

EL Number
(Norway) 4315257

| General specifications | |
|--|--|
| Product name | Eaton Moeller® series M22 Accessory LED luminous ring |
| Part no. | M22-XPV60-Y-230 |
| EAN | 4015081350605 |
| Product Length/Depth | 25 millimetre |
| Product height | 60 millimetre |
| Product width | 60 millimetre |
| Product weight | 0.035 kilogram |
| Compliances | Contact Manufacturer |
| Certifications | CE CSA-C22.2 No. 14-05 CSA Class No.: 3211-03 CSA-C22.2 No. 94-91 UL CSA UL File No.: E340491 CSA File No.: 012528 IEC/EN 60947-5 UL Category Control No.: NISD UL 508 |
| Product Tradename | M22 |
| Product Type | Accessory |
| Product Sub Type | LED luminous ring |
| Catalog Notes | One group of 8 LEDs (series-connected) |
| Features & Functions | |
| Color | Yellow |
| General information | |
| Accessory/spare part type | Accessory |
| Degree of protection | IP66 IP69 |
| Type | Emergency stop operator accessory |
| Used with | Modular pushbutton |
| Climatic environmental conditions | |
| Ambient operating temperature - min | -25 °C |
| Ambient operating temperature - max | 70 °C |
| Electrical rating | |
| Rated operational voltage | 230 V AC |
| Communication | |
| Connection to SmartWire-DT | No |
| Actuator | |
| Actuator diameter | 60 mm |
| Contacts | |
| Force for positive opening - min | 0 N |
| Design verification | |
| Equipment heat dissipation, current-dependent P _{vid} | 0 W |
| Heat dissipation capacity P _{diss} | 0 W |
| Heat dissipation per pole, current-dependent P _{vid} | 0 W |
| Static heat dissipation, non-current-dependent P _{vs} | 0.65 W |
| 10.2.2 Corrosion resistance | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | Meets the product standard's requirements. |

| | | | |
|--|--|--|--|
| 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects | | | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | | | Please enquire |
| 10.2.5 Lifting | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | | | Meets the product standard's requirements. |
| 10.3 Degree of protection of assemblies | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | | | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | | | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | | | Is the panel builder's responsibility. |
| 10.9.2 Power-frequency electric strength | | | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | | | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | | | Is the panel builder's responsibility. |
| 10.10 Temperature rise | | | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 Electromagnetic compatibility | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 Mechanical function | | | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 9.0

| | | | |
|--|--|--|---------------|
| Low-voltage industrial components (EG000017) / Accessories/spare parts for command devices (EC002024) | | | |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Command and alarm device / Command and alarm device (accessories) (ecl@ss13-27-37-12-92 [AC0037015]) | | | |
| Type of electrical accessory/spare part | | | Diode element |
| Type of mechanical accessory/spare part | | | Other |
| Accessory | | | Yes |
| Spare part | | | No |