

DATASHEET - 3.6KV 63A 2" 'J' MOTORSTART FUSE



Motor fuse-link, medium voltage, 63 A, AC 3.6 kV, 50 kA, DIN 43625 2", 51 x 192 mm, back-up, DIN, with striker



Part no. 3.6KV 63A 2" 'J' MOTORSTART FUSE
Catalog No. 3.6WDOSJ63

Similar to illustration

Delivery program

Product range			Fuse
Basic function			Motor fuse-link
Field of application			medium voltage
Rated current	I	A	63
Rated voltage			AC 3.6 kV
Construction size			DIN 43625 2"
Size			51 x 192 mm
Utilization category			back-up
Status indicator			with striker
Breaking Capacity		kA	50
usable for size/applications			motor protection
Standard/Approval			DIN
Shape			cylindrical
Standards/Regulations			DIN 43625 VDE 0670-4 IEC 60282-1

Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	63
Rated voltage		kV	3.6
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	50
Utilization category			Other
Application			Motor protection
Length		mm	254
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			Yes
Standard			DIN
Release characteristic			Other
Installation technique			Air