

PRODUCT-DETAILS

N2201.2 PL

Switch 1-way Double Pole Rocker/button 2pole switch with LED exchangeable Silver -Zenit



General Information	
Extended Product Type	N2201.2 PL
Product ID	2CLA220120N1301
EAN	8427238070162
Catalog Description	Switch 1-way Double Pole Rocker/button 2-pole switch with LED exchangeable Silver - Zenit
Long Description	Color: Silver. Rated voltage: 110 - 250 Vac Rated current: 16 AX. Rated power iLED (230/127 Vac): 200/100 W. Screwless terminals Optional: locator LED lamp N2192.1 BL (127 Vac) or N2192 RJ (230 Vac) Size: 2 modules.

Installation	
Instructions and	2CLX210109N1001
Manuals	

Technical	
Data Sheet, Technical Information	9AKK10103A5108

N2201.2 PL 2

Function	Function lighting: Orientation
Rated Voltage (U _r)	250 V
Rated Current (In)	16 A
Maximum Switching Current	Fluorescent Lamps 16
Number of Rocker Switches	1
Design Range	Zenit
Wiring Configuration	2-pole switch
Actuator Type	Rocker/button
Connection Type	Plug Clamp
Lamp Type	LED exchangeable
Mounting Type	Flush Mounted
Type of Fastening	Engage (Snap)
Surface Finishing	Decor Matt
Material	Plastic Thermoplastic
Label Space Provided	No
Illumination	Optional
Color	Silver
Number of Batteries	0

			
Env	ıror	ıme	ntal

Ambient Air	Operation -5 +35 °C
Temperature	Storage -5 +50 °C
Degree of Protection	IP20
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
RoHS Information	2CLC220120N1301
REACH Declaration	9AKK108467A7464
Conflict Minerals	9AKK108468A3363
Reporting Template	
(CMRT)	

Dimensions

Product Net Width	44 mm
Product Net Height	44 mm
Product Net Weight	0.036 kg

Ordering

Replaced Product ID 2CLA220120N1302 (OLD)

Certificates and Declarations

Declaration of 9AKK106930A5900
Conformity - CE

Classifications

N2201.2 PL 3

ETIM 8	EC001590 - Installation switch
ETIM 9	EC001590 - Installation switch
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85365080
UNSPSC	39122226

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Wiring\ Accessories\ -\ Light\ Switch\ Ranges \rightarrow Cover\ Plates\ and\ Control\ Elements \rightarrow Mechanical\ Controls$





