

PRODUCT-DETAILS

N2204.8 PL

Pushbutton None Single push button Rocker 1 pole, 1NO 0NC 1CO Silver - Zenit



General Information

Extended Product Type	N2204.8 PL
Product ID	2CLA220480N1301
EAN	8427238138664
Catalog Description	Pushbutton None Single push button Rocker 1 pole, 1NO 0NC 1CO Silver - Zenit
Long Description	Color: Silver. Rated voltage: 110 - 250 Vac Rated current: 16 A Screwless terminals 1-gang, 1-way - Normally Opened (NO) contact Optional: locator LED lamp N2191. Size: 2 modules.

Installation

Instructions and Manuals	2CLX210109N1001
--------------------------	-----------------

Technical

Data Sheet, Technical Information	9AKK10103A5108
Rated Voltage (U_r)	250 V
Rated Current (I_n)	16 A
Contacts Configuration	1 NO, 0 NC

Number of Poles	1
Number of Contacts CO	1
Number of Contacts NC	0
Number of Contacts NO	1
Number of Rocker Switches	1
Design Range	Zenit
Actuator Type	Rocker
Connection Type	Screwless
Mounting Type	Flush Mounted
Type of Fastening	Engage (Snap)
Surface Finishing	Decor Glossy
Material	Plastic Thermoplastic
Legend	None
Model Number	Single push button
Color	Silver
Number of Batteries	0

Environmental

Ambient Air Temperature	Operation -5 ... +35 °C Storage -5 ... +50 °C
Degree of Protection	IP20
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Dimensions

Product Net Width	44 mm
Product Net Height	44 mm
Product Net Depth / Length	25 mm
Product Net Weight	0.032 kg
Built-In Depth (t ₂)	25 mm

Ordering

Replaced Product ID (OLD)	2CLA220480N1302 2CLA220480N1303
---------------------------	------------------------------------

Certificates and Declarations

Declaration of Conformity - CE	9AKK106930A5900
--------------------------------	-----------------

Classifications

ETIM 8	EC000029 - Push-switch button
ETIM 9	EC000029 - Push button
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85365080

Categories

Low Voltage Products and Systems → Wiring Accessories - Light Switch Ranges → Cover Plates and Control Elements → Mechanical Controls

