

PRODUCT-DETAILS

6596

Compensator 250 V



Informações gerais

| | |
|--------------------------|-------------------|
| Tipo de produto alargado | 6596 |
| ID do produto | 2CKA006599A2290 |
| EAN | 4011395638507 |
| Descrição do catálogo | Compensator 250 V |

Descrição longa

Prevents the self-ignition of energy-saving or LED lamps during switching with orientation illumination (parallel to the lamp). Prevents after-glow of low-voltage halogen or LED lamps in a deactivated state due to possible ripple voltage or activation via touch-dimmer without neutral conductor connection (parallel to the primary transformer side or to the lamp). Removes noise generation on electronic transformers in a switched-off state during activation via touch-dimmer without neutral conductor connection (parallel to the primary transformer side). Removes ripple voltages on the control line in blind control/group controls (parallel between control wire "UP" and neutral conductor as well as "Down" and neutral conductor). Dimensions: diameter 22 mm, length 25 mm, length of the connecting cable approx. 235 mm.

Installation

| | |
|----------------------|--------------------|
| Instruções e Manuais | No document needed |
|----------------------|--------------------|

Technical

| | |
|---------------------------------------|-----------------------------------|
| Ficha de dados, informação técnica | No document needed |
| Tensão nominal (U _r) | 250 V |
| Frequência nominal (f) | 50 Hz |
| Tipo de apoio | Built-in |
| Application Function | Electrical Load and Light Control |

Environmental

| | |
|---|--|
| Estado RoHS | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |
| Informação RoHS | 2CKA200000E6001 |
| REACH Declaration | 2CKA309999E9999 |
| Conflict Minerals Reporting Template (CMRT) | 9AKK108468A3363 |

Dimensions

| | |
|---|---------|
| Largura Líquida do Produto | 21.9 mm |
| Altura Líquida do Produto | 21.9 mm |
| Profundidade/Comprimento Líquidos do Produto | 26 mm |
| Peso Líquido do Produto | 16.5 g |

Ordering

| | |
|---|-------------|
| ID de Substituição do Produto (ANTIGA) | 6599-0-2290 |
|---|-------------|

Certificates and Declarations

| | |
|-----------------------------------|-----------------|
| Declaração de conformidade -CE | 2CKA100000E1711 |
|-----------------------------------|-----------------|

Classifications

| | |
|----------------|---|
| ETIM 8 | EC002649 - Accessories/spare parts for domestic switching devices |
| ETIM 9 | EC002649 - Accessories/spare parts for domestic switching devices |
| Categoria REEE | 5. Small Equipment (No External Dimension More Than 50 cm) |
| REEE B2C / B2B | Business To Consumer |
| CN8 | 8536 49 00 |

Categorias

Produtos e Sistemas de Baixa Tensão → Wiring Accessories - Light Switch Ranges → Accessories → Accessories Electronics

